

HDMI-HD-M

Full HD 4K HDMI Video Converter



Overview

TVI to HDMI video converter that is used to display live 1080p high definition video from TVI security cameras on a HDMI TV monitor for public view monitors or to DVR. In addition to TVI cameras, the converter also works with CVBS cameras, CVI 4MP, AHD 5MP. This works with all HD-TVI video resolutions. The HDMI video output is 1080p resolution. There are BNC Video Input, BNC Video Loop Out, and 1080p HDMI Out connections. Easy to use, plug and play, strong compatibility.

Features

- Supported CVI 4MP, AHD 5MP Camera
- Auto recognition 720P/1080P/3MP/4MP/5MP/8MP resolution, indicator visual display
- TVI+CVBS to HDM, HDMI output
- HDMI Output Resolution: 1080p 60Hz, HD-LINK light
- Support transmission distance up to 300m over coaxial cable

Specifications

Model	HDMI-HD-M
Material	Metal
Dimension	3.74" (L) x 2.83" (W) x 0.94" (H)
Weight	13.1 ounces
CVBS	1 channel BNC input (NTSC/PAL), PTZ control, RS485 control, Baud 600-115200bps, compatible with more than 30 protocols
Power Source	5V
Operating Temperature	-10°C~60°C / -14°F~140°F
Supported HD-TVI Camera Resolutions & Frame Rates:	720p @ 25/30/50/60 FPS 1080p @ 25/30 FPS 3 MP (2048 x 1536) @ 18/25/30 FPS 4 MP 2688 x 1520p @ 15 FPS 4 MP 2560 x 1440p @ 12/25/30 FPS 5 MP 2592 x 1944p @ 12.5/20 FPS 4K (8 MP) 3840 x 2160 @ 15 FPS